

# MG5050XB6A

## Magellan 32-Zone Wireless Transceiver Control Panel

- 2 serial outputs master/slave
- M2 two-way FSK hardware ready
- 8 on-board zones (16 with ATZ)
- Built-in transceiver (433 MHz or 868 MHz)
- Expandable to 32 zones, 2 partitions, 32 users and 32 remotes
- 4-wire communication bus (connect up to 15 modules)
- Supports IP and cellular IP reporting
- Supports VDMP3 (landline only)
- Supports 16 PGMs (any of which can be wireless)
- App-based system control via [BlueEye](#)
- In-field firmware upgrade via [307USB](#) And [BabyWare](#) remote or local
- Menu-driven programming for the Installer, Master and Maintenance codes
- Multiple telephone numbers for event reporting: 3 monitoring and 5 for Personal Dialing
- Calendar with Daylight savings Time
- StayD Mode
- Sleep arming method
- RF Jamming Supervision
- 512 events buffered
- Fits in a 20 x 25.5 x 7.6 cm (8 x 10 x 3 in) metal box or in a 28 x 28 x 7.6 cm (11 x 11 x 3 in) metal box
- CE

